

Date: <July - 2006>

Document No.: +95-123603

SETUP PROCEDURE:


This procedure describes how to reset the EXPLORER™ 500 to Factory Default.

Connecting via the USB interface using Hyper Terminal:

Start Control panel – ‘Phone a Modem Options’


Select ‘Modems’ and note the COM port assigned to ‘Thrane & Thrane EXPLORER™ 500 port 1.’

Ex.: (COM port no’s may vary)



In the HyperTerminal menu

- Select ‘File->Properties’
- Select ‘Connect using’ the new COM port listed in ‘Phone and Modem Options’ above.
Do NOT select! ‘Thrane & Thrane EXPLORER™ 500 port x’, you MUST select a ‘COM’ port.



Note: The number on the com port you have to select may have changed after the installation of the new USB driver!

Test that you have selected the right COM port.

- **Write** in HyperTerminal the AT command 'ATI'.
- **Response** from the AT shell should be: 'Thrane & Thrane'
- **Write** following at-command: 'at+cmar=1234'
- **Response** from the AT shell 'OK'


- **In the HyperTerminal menu**
- **Select** 'Call->Disconnect'

The EXPLORER™ 500 will now reboot and after the reboot the all settings will be reset to factory default.


Connecting via the Ethernet interface using Hyper Terminal:

Connect a pc to the EXPLORER™ 500 via the Ethernet interface

- In the HyperTerminal menu
- Select 'File->Properties'
- Select 'TCP/IP (Winsoc)



- Host Adr: 192.168.0.1
- Port no.: 5454




- Write the following at-command: 'at+cmr=1234'
- Response from the AT shell 'OK'

The EXPLORER™ 500 will now reboot and after the reboot the all settings will be reset to factory default.

Connecting via the Ethernet interface using a command Prompt:


Connect a pc to the EXPLORER™ 500 via the Ethernet interface

- Open a command prompt (start->run->cmd)
- Run: telnet 192.168.0.1 5454



```
C:\WINNT\system32\cmd.exe
Microsoft Windows 2000 [Version 5.00.2195]
(C) Copyright 1985-2000 Microsoft Corp.
C:\Documents and Settings\ocn>telnet 192.168.0.1 5454_
```

- **Write** the following at-command: 'at+cmar=1234'
- **Response** from the AT shell 'OK'



```
C:\WINNT\system32\cmd.exe - telnet 192.168.0.1 5454
at+cmar=1234
OK
```

The EXPLORER™ 500 will now reboot and after the reboot the all settings will be reset to factory default.

Thrane & Thrane
After Sales Service

*Information in this document is subject to change without notice
and does not represent a commitment on the part of Thrane & Thrane A/S.
© 2005 Thrane & Thrane A/S. All rights reserved.
Printed in Denmark.*